TEMPERATURE TRANSMITTER

Type: Ex for zone 0, 1 or 2, EEx ia IIC

T1...T6, programmable

Input: Pt100...Pt1000 or Ni100...Ni1000

Type: TT-5332D

Sheet No. 6-5 V2.1

10122-E010818V2.1



Application:

- Temperature linearised measurement with Pt100...Pt1000 or Ni100...Ni1000.
- Conversion of linear resistance change to standard analogous current signal, e.g. from valves or ohmic level sensors

Properties:

- High measurement accuracy
- RTD- 2, 3 or 4 conductor attachment
- The RTD and resistance inputs have cable compensation for 3 conductor attachments
- Programmable sensor error value
- Can be programmed within a few seconds by 2-way configuration (Windows), to measure temperatures within all RTD ranges defined by the norms
- TAG No: 15 character configurable
- Degree of protection (case/clamp): IP68 / IP00
- Measurements: Ø44 x 20.2mm
- Mounting/ installation: can be mounted in DIN form B sensor head or on DIN track with special clamp



TECHNICAL DATA:

INPUT:

Type	Min temp.	Max temp.	Min span	Norm
Pt100	-200°C	+850°C	25°C	DIN IEC 751
Ni100	-60°C	+250°C	25°C	
Lin. R	0Ω	10000ohm	30ohm	

COMMUNICATION INTERFACE:

Loop link 5905

MECHANICAL DATA:

Measurements: Ø 44 x 20,2 mm

Degree of protection (case/clamp): IP68/ IP100

ENVIROMENTAL CONDITIONS:

Operating temperature: -40°C to +85°C Humidity: < 95% RH (non-cond.)

TECHNICAL DATA:

OUTPUT:

Signal range: 4 - 20 mA

ACCURACY:

Type:	Basic	Temperature
	accuracy:	coefficient:
RTD	<u><</u> ±0,2°C	<±0,01°C/°C
LIN R	<±0,1ohm	<±10mohm/°C

COMMON SPECIFICATIONS:

Supply voltage: DC: 7,2...35 V

Voltage drop: 7,2 VDC

Reaction time (programmable): 0,33...60 s

SENSOR TROUBLE SHOOTING:

Programmable: 3.5...23 mA NAMUR NE43 Upscale: 23 mA NAMUR NE43 Downscale: 3,5 mA

Ordering details: Please state If the transmitter

should be programmed

Transmitter Input Type:			
4 mA =	C°	20 mA =	C°





2-wire programmable RTD transmitter

5332D

- RTD or Ohm input
- Accuracy: Better than 0.05% of selected range
- Programmable sensor error value
- For DIN form B sensor head mounting





















Application


- Linearized temperature measurement with Pt100...Pt1000 or Ni100...Ni1000 sensor.
- · Conversion of linear resistance variation to a standard analog current signal, for instance from valves or Ohmic level sensors.

Technical characteristics

- · Within a few seconds the user can program PR5332D to measure temperatures within all ranges defined by the norms.
- Dedicated programmable non-isolated 4-wire RTD
- RTD and resistance inputs have cable compensation for 2-, 3and 4-wire connection.
- · Continuous check of vital stored data for safety reasons.

Mounting / installation

· For DIN form B sensor head mounting.



Order

Туре	Version	
5332	Hazardous area, Zone O / Dlv. O, ATEX, IECEx, FM, CSA	: D

Environmental Conditions

Operating temperature	-40°C to +85°C
Calibration temperature	2028°C
Relative humidity	< 95% RH (non-cond.)
Protection degree (encl./terminal)	IP68 / IP00

Mechanical specifications

Dimensions	Ø 44 x 20.2 mm
Weight approx	50 g
Wire size	1 x 1.5 mm ² stranded wire
Screw terminal torque	0.4 Nm

Common specifications

Su	n	nl	v

Supply voltage	7.230 VDC
Internal power dissipation	25 mW0.7 W

Response time

Response time (programmable)	160 s
Voltage drop Warm-up time Programming Signal / noise ratio EEprom error check Accuracy	5 min. Loop Link Min. 60 dB < 3.5 s Better than 0.05% of selected
Signal dynamics, input	16 bit < 0.005% of span / VDC < ±0.5% of span

Input specifications

Common input specifications	
Max. offset	50% of selected max. value

RTD input RTD type...... Pt100, Ni100, lin. R

Cable resistance per wire	5 Ω (max.)
Sensor current	Nom. 0.2 mA
Effect of sensor cable resistance	
(3-/4-wire)	$< 0.002 \Omega / \Omega$
Sensor error detection	Vac

Linear resistance input

Linear resistance minmax	0 Ω5000 Ω

Output specifications

Updating time	440 ms
Current output	
Signal range	420 mA
Min. signal range	16 mA
Load (@ current output)	\leq (Vsupply - 7.2) / 0.023 [Ω]
Load stability	\leq 0.01% of span / 100 Ω
Sensor error indication	Programmable 3.523 mA
NAMUR NE43 Upscale/Downscale	23 mA / 3.5 mA

of span.... = of the presently selected range

I.S. / Ex marking

= 1	
ATEX	II 1 G Ex ia IIC T4T6 Ga, II 1
	D Ex ia IIIC Da, I M1 Ex ia Ma
IECEx	Ex ia IIC T4T6 Ga, Ex ia IIIC
	Da, Ex ia I Ma
FM, US	
	T4/T6; Cl. I Zone 0, AEx ia IIC
	T4/T6; Cl. 1, Div. 2, Gp. A, B,
	C, D, T4/T6
CSA	
	ia IIC, Ga

Observed authority requirements

Directive

Directives	
EMC	2014/30/EU
ATEX	2014/34/EU
RoHS	
EAC	TR-CU 020/201
EAC Ev	TD CI1012/201

Approvals

ATEX	KEMA 06ATEX0062X
IECEx	DEK 13.0035X
FM	FM17US0013X
CSA	1125003